



Thank you for choosing our product(s). Our Company is actively involved in every step of the production. Our product(s) are designed to be utilized for every

application that graces your home or business. We pride ourselves in providing the most prompt and courtesy service to all of the valued customers.

Please find the enclosed detailed instruction and read carefully for proper installation.

If you have any questions, please contact the retailer Where the purchased was made.



1109F10 D10" H6.5" L3

SAFETY

Warning: MAKE SURE THE ELECTRICITY TO THE WIRES YOU ARE WORKING ON IS SHUT OFF.BY EITHER REMOVING THE FUSE OR TURNING OFF THE CIRCUIT BREAKER.

CAUTION

- Before assembling the lighting fixture, please read all instructions carefully.
- All frame & crystal components are fragile, please handle with care.
- Required supply circuit : 110 130V/60Hz
- Labeled wires are "L" for live wire, "N" for neutral wire, "E" for ground wire.
- Never install fixture on damp ceiling, the room should be dry and well ventilated
- All electrical components must be installed by a licensed electrician and in accordance with the National Electrical Code and the appropriate local electrical codes.

Unpack the Package


Please open the box carefully and check all the items are inside the box. If you have any installation, assembling and missing parts questions.

where you purchase from and any other relevant information ready, our customer service team will provide comprehensive and worry free service to our valued customers.

(01)

Frame Assembly Diagram

1109F10 D10" H6.5" L3



(02)

1109F10 D10" H6.5" L3

Step 1

Please use the parts list to ensure you are not missing any parts.

		PARTS LIST		
Part #	Picture	Description	Qty	Check list
P1		Crossbar 4″ (Canopy part)	1	
P2		5/32-32 Screw	2	
Р3		Power Cord 20" SPT-1	1	
P4		Black/Gold/Clear D4.75" Canopy plat	1	
Р5		E12*3 Socket	1	
P6	0	Socket Ring	3	
P7	\bigcirc	D10"Metal Ring	1	
P8	B	Set nut	1	
Р9	\bigcirc	metal washer	1	
P10		thread pipe	1	
P11		Mid Column	1	
P12	۲	NUT	2	
P13	•	Metal tube	1	
P14	Ø	D3.35"Metal Ring	1	
P15	\odot	D3.15"Round Metal plate	1	

1109F10 D10" H6.5" L3

Part #	Picture	Description	Qty	Check list
P16	ø	Cap nut	1	
А	***	24#*1+20#*1+16#*2 +14#*1+12#*1+10#*1	25	


1109F10 D10" H6.5" L3

Step 2

Canopy Installation Instruction

 $\ensuremath{\mathsf{IMPORTANT}}$: Test sockets with bulb before dressing the fixture.

- $\boldsymbol{1}$. Attach the crossbar to the electrical box.
- 2 .Pull wires up through the nipple.
- 3 .Attach the fixture to the ceiling.
- 4 .Make the electrical connections as detailed in the drawing above.



1109F10 D10" H6.5" L3

 $_{\rm Step \ 3}^{\rm Step \ 3}$ Frame Assembly Instructions


1.Install the metal plate(5), metal ring(4) and metal tube(3) to the lamp body(1) with the cap nut(6).2.Attach the fixture to the ceiling by nut(2).3. Install E12 light source, no include bulb.

The end!

Step 4

Crystal Dressing Diagram 1.Hanging crystal(A)on the fixture

When dressing the chandelier with the crystals please remember to wear either rubber or cotton gloves. So as to prevent any damage or smudging on the crystals.



Congratulations !

You are now done installing your Elegant Lighting fixture. Sit back and admire each crystal as it will become the statement piece for your room/house.

Thank you.

1109F10 D10" H6.5" L3

Cleaning and Maintenance of Chandelier Frame The finish on our chandelier frames and fixture frames is protected by a durable coating of lacquer. To clean, use a clean soft, dry cloth. Do not use any metal polishes, cleaners, abrasives or any substance which could remove the protective finish. Failure to follow these instructions automatically voids the guarantee.

Cleaning and Maintenance of Crystals Wet a soft cotton fabric in clean warm water and wipe gently, then polish with a dry soft cotton fabric.

To Order Crystal Replacement Parts Should you require replacement crystals or pins (the metal connectors attaching the crystals), contact the store where the product was purchased or contact us . For ease of ordering, you may use the original crystal trimming instructions provided with this product and circle the items you wish to order, indicating the quantity by writing the number needed adjacent to the circle . You will be contacted with prices prior toshipment. All orders must be pre-paid.

(08)

Elegant Lighting Warranty

The finish and frame of your new chandelier or fixture are warranted for a period of one (1) year from the date of purchase. Our company will, at its option, repair or replace any frame that has a defect in the materials or workmanship during the warranty period. All crystals are guaranteed for their original quality during the life of the chandelier. Breakage is not covered by this warranty.

To make a claim under this warranty, contact our customer service department. A written return authorization form will be sent to you with specific instructions. 1109F10 D10" H6.5" L3

Returns and Conditions of Warranty

Returns must be pre-authorized by contacting our customer service department . Returns will only be accepted with a written return merchandise authorization and return shipping charges pre-paid. We researve the right to inspect all returned merchandise to fully determine the nature of any defect. This guarantee shall not apply to any product that has been changed, altered or otherwise modified, nor shall it apply to any product that has been repaired or altered by anyone other than a pre-authorized facility. We will not be responsible for any breakage or damages incurred during transit, nor for crystal parts or metal frame part that have been subject to misuse, negligence, accident or inappropriate handling. Also, we will not be held responsible for damage incurred during improper installation or wiring by others, nor for damages resulting from a failure to follow the recommended maintenance or installation procedures. This guarantee is issued in lieu of any and all other guaranteed or warrantee, whether written or implied and any and all other obligations or liabilities. Further, we neither authorize nor permit any other person or firm to assume for us, any liability in connection with the sale of our products.

10